



One Button Operation



Oxygen Level



Easy to Use



Accurate Reading



Pulse Rate

FTP-102 Fingertip Pulse Oximeter

Features:

- With beep pulse sound and alarm for SpO₂, Pulse Rate and Perfusion Index.
- Low battery alarm display, Auto power-off.
- SpO₂ and pulse monitoring, and waveform display.
- Runs on standard AAA batteries.
- HD LED display, 3 level adjustable brightness.
- Low power consumption, continuously work for 50 hours.

Specifications:

Display Type
Power Requirements

LED Screen
Two AAA alkaline batteries

SpO₂

Measure range: 35-99%
Resolution: 1%
Accuracy: 70%- 100%. ±2%
35%-69% no definition

Pulse Rate

Measure range: 35-250 bpm
Resolution: 1bpm
Accuracy: ±2bpm
Pulse intensity: bar-graph

Environment Requirements

Operation temperature: 5~ 40 °C
Storage temperature: -10~ 50 °C
Ambient humidity: 15-80%

How to Use:



Open the pulse oximeter



Place your finger in the oximeter



Press the power button



Wait for the results.

Contact us:



Mobile No./ WhatsApp No. : +91 9310113243



Web : www.klifacare.com



Email : info@klifacare.com

Kannu Impex (India) Pvt. Ltd.

412, Suncity Trade Tower, Sector-21, Gurugram-122015