



One Button Operation



Oxygen Level



Easy to Use



Accurate Reading



Pulse Rate



FTP-104 Fingertip Pulse Oximeter

Features:

- Measure blood oxygen saturation level and pulse rate.
- Low battery indicator.
- One button operation, Automatic power-off.
- PR waveform display.
- OLED display.
- Four directions modes.
- Low power consumption.

Specifications:

Display Type
Power Requirements

OLED Screen
Two AAA alkaline batteries

SpO₂

Measure range: 35-100%
Resolution: 1%
Accuracy: 70%- 100%. ±2%
35%-69% no definition

Pulse Rate

Measure range: 35-250 bpm
Resolution: 2bpm
Accuracy: ±2bpm
Pulse intensity: bar-graph

Environment Requirements

Operation temperature: 5~ 40 °C
Storage temperature: -20~ 55 °C
Ambient humidity: 15-85% non-condensing

How to Use:



Open the pulse oximeter



Place your finger in the oximeter.



Press the power button



Wait for the results.

Contact us:



Mobile No./ WhatsApp No. : +91 9310113243



Web : www.klifecare.com



Email : info@klifecare.com

Kannu Impex (India) Pvt. Ltd.

412, Suncity Trade Tower, Sector-21, Gurugram-122015