
ES-XW1E-LV412Q4MFR (ORDER NO. 105014)

Emergency stop ES-XW, built-in devices, 22 mm

- ▶ Button head, red, 40 mm ø
- ▶ Contact block monitoring
- ▶ Reset by pulling or turning
- ▶ illuminated




Description


Switching element

- ▶ 2 NC \ominus + 1 NO


Function drawings



Dimension drawings



Connection examples



Technical data

Approvals

--	--	--

Electrical connection ratings

Operating current	15 mA
Operating voltage	AC/DC -10% ... 24 ... +10% V
Rated insulation voltage U_i	250 V
Switching current	min. at 24 V 10 mA
thermal rated current I_{th}	1 A
Utilization category	
DC-14 Normally open contact	0.3 A 250 V
DC-13 Normally closed contact	1A 30V
AC-15 Normally closed contact	1.5 A 250 V

Mechanical values and environment

Ambient temperature	-25 ... +55 °C
Connection	Screw terminal
Degree of protection	IP20
Material	
Pushbutton	reinforced thermoplastic
Housing	Polycarbonate
Contact	Silver alloy, gold flashed
Mechanical life	0.25 x 10 ⁶
Mounting type	IEC 947-5-1 D22
Number of NO contacts	1
Number of positively driven contacts	2

Reliability values according to EN ISO 13849-1

B10d	0.1 x 10 ⁶
------	-----------------------

Miscellaneous

Additional feature	
	Reset by pulling or turning
	Button head Ø 40 mm
	Contact block monitoring
Color	
Actuating button	Red transparent
Bottom part	yellow
Lighting	yes

Accessories

Mounting accessories

Emergency stop plate – blank – for 40 mm buttons on ES-XW devices



157255
ES-HWAV-0

- ▶ Emergency stop plate – blank – for 40 mm buttons on ES-XW devices

Key for emergency stop ES-XW

106337
ES-MW9Z-T1

- ▶ Key for fastening the ring screw on ES-XW... devices

Plate for emergency stop ES-XW



106340
ES-HWAV-27

- ▶ Emergency stop plate for 40 mm buttons on ES-XW devices with text "Emergency Stop"

Contacts

🏠 EUCHNER GmbH + Co. KG
Kohlhammerstraße 16
70771 Leinfelden-Echterdingen

☎ +49 711 7597-0

📠 +49 711 753316

✉ info(at)euchner.de