

AROINDIA
ELECTROMECH PVT. LTD.

Operating Instruction Manual

Ken Kou - Shoe Cover Dispenser

Model: SR-M (031)



Product Introduction

The shoe film machine is very practical and has a wide range of application. It is not only suitable for families, but also widely used in hotels, real estate, hospitals, electrical; exhibition halls, dust-free workshops of factories, animal and plant breeding research sites, etc. This product does not require any power supply. Safe and reliable, exquisite shape, no need to take off shoes, easy and convenient to change the film

1. Correct demonstration of film cutting



2. Shoe film Installation steps



①



②

Step 1: Lift the cover and put it a side

Step 2: Pick up a roll, align the small

testers on both sides with the card slots on both sides of the machine and put it down (the left and right sides must be placed in the card slot)



Step 3: Put the shoes out and spread them evenly on the rough seabed.

Note: the glued side of the shoes faces up, and the non -finished side sticks to the sponge pad, so that the most precious scroll cover will stick to it cover.

3. Shoe film machine using steps

Step 4: First use one foot to step on the paved shoe film with a little force, pull the foot that is stuck to the toe back, and pull it to the black cover of the rear training (be careful not to cast too long, so as not cut it) set is the best way to stick to the machine and push it down a little bit, and it will be changed and cut off



Precautions of use

In order for you to use this product better, please use it according to the following precautions:

1. When installing the shoe film, put the glued side up, and the non-stick side look at the sponge pad on one side, don't reverse it, so that it can stick to the sole.
2. When sticking the shoe film, pull it back slowly, and the length of the shoe should not exceed pass the black pedal so as not to effect the cutting film.
3. Because the film cutting blade is sharp, don't touch it with your hands, and be careful not to let children hold it.

After-Sales Service

Every shoe film machine of our company has been strictly tested and generally will not fail. If there is a problem with the during use , you can also contact our company directly, it best to avoid damage to the machine.

Specification:

Product size	: 60x26x8cm (23.62*10.24*3.15inch)
Product weight	: 2.65kg (5.84lb)
Place of use	: home/hotel/office building, etc.
Working method	: pedal type
Product material	: ABS plastic
Product features	: easy to use, no space
Shoe mold size	: length 90m*width 15cm (35.43*5.91inch) (outer diameter of shoe mold roll 10cm/3.94inch)
Applicable maximum shoe size	: US shoe size 11/China shoe size 47 (length 28.5cm/11.22inch)

Aroindia Electromech Pvt Ltd.

Address: A-117, 1st Floor, Near Metro Pillar -783, Sewak Park

Dwarka Mor, New Delhi – 110059

Phone: +91 9818366017, 9599591802, **E-mail:** support@aroindia.com

www.aroindia.com